1 SERVO MOTOR MAINTENANCE

1.1 SERVO MOTOR MAINTENANCE PARTS

1.1.1 Pulsecoder

The following lists the ordering specification numbers for maintenance.
(1) Pulsecoder: ordering specification

Motor model	Motor specification		Pulsecoder: ordering specification		
βiS-B series βiF-B series	A06B-2aaa-BccX A06B-2aaa-BccX #0100	X=3	A860-2070-T321	βiA1000	Standard specification IP67 specification Common
βiSc-B series	A06B-2aaa-BccX A06B-2aaa-BccX #0100	X=7	A860-2070-T371	βiA1000 (dedicated to the βiSc-B)	Standard specification IP67 specification Common

(aaa, cc : Any)

Motor model	Motor specification		Pulsecoder: ordering specification		
βiS series βiF series	A06B-0aaa-BccX	X=3	A860-2020-T301	βiA128	Standard specification
	A06B-0aaa-BccX #0100	X=3	A860-2020-T321	βiA128	IP67 specification
βiSc series	A06B-0aaa-BccX	X=7	A860-2020-T361	βiA128 (dedicated to the βiSc)	Standard specification
	A06B-0aaa-BccX #0100	X=7	A860-2020-T371	βiA128 (dedicated to the βiSc)	IP67 specification

(aaa, cc : Any)

(2) Oldham's coupling: ordering specification

Motor model	Motor specification	Oldham's coupling: ordering specification
βiS-B series βiSc-B series βiF-B series	A06B-2aaa-BccX	A290-0501-V535
βiS series βiSc series βiF series	A06B-0aaa-BccX	

(aaa, cc, X : Any)

NOTE
Problems concerning the Pulsecoders of the motors listed in the table below require the maintenance (replacement) of the entire motor.
(It is not possible to maintain the Pulsecoder alone.)

JR AUTOMATION TECHNOLOGIES INC*
JDOWLING